

Short Operating Instruction for Digital Recorder EDIC-mini Tiny 16 A63 — 300h/600h/1200h

Overlook

Miniature digital Recorder EDIC-mini Tiny 16 A63 is a professional device intended for making high quality record of voice messages into a built-in flash memory. The recordings can be further uploaded onto the PC. The Recorder can be used as a flash media to store and transfer data of any standards (under “RecManager” control).

Specifications:

- VAS (Voice Activating System) to compress pauses while recording;
- Circular recording mode;
- Built-in real time clock;
- Timers to start recording at the preset time;
- Information protection system;
- Automatic Gain Control (AGC) system.

Supplied Software makes it possible to:

- Save the recorded messages on the PC as standard sound files;
- Restore deleted pauses when uploading files onto the drive;
- Set the recorder's parameters;
- Apply password protection of the access to the recorder's settings and information;
- Update software.
-

Recorder's Appearance



Technical Characteristics:

Last digits in the models' names specify the maximum recording duration in hours (built-in memory capacity) for the recording mode: sample rate 8 kHz, and 2 bit ADPCM.

- Battery life in record mode — (8 KHz, without compression) at fully charged battery — up to 40 hours;
- Battery life in stand-by mode — up to 3,5 months;
- Battery life in record mode with VAS (audio signals below threshold) — up to 140 hours;
- Exchange rate — up to 0, 7 Mb/s
- Frequency band — 0,1-10 kHz
- Signal-to-noise ratio — -80 dB
- Built-in microphone sensitivity — 10–12 m
- Storage life of built-in flash memory — up to 10 years
- Power supply, battery capacity — Li-Pol, 140mAh
- Case — metallic
- Dimensions — Ø 14x78 mm
- Weight — 28 g
- Operating temperature range — 0–40 °C
- Operating lifetime — 5 years.
- OS supported: Windows XP / Vista / 7.

Recorder's Functional Testing

Starting Recording. To start or stop recording keep the Record button pressed for about 2 seconds until the LED flashes five times. When the recorder stops recording, the LED flashes once.

Playing back the Recording. Connect USB cable to the Recorder, then to the USB port of the PC. The system recognizes a new storage device. Launch «RecManager.exe». The content of the Recorder is on the left side of the window. Select the recording, right-click and select "Copy to PC" in the context menu. The recording will be converted to WAV and appears at the right side of the window. To play back the recording left-click it twice.

Instructions. Operating instructions for the Recorder and "RecManager" are located in the internal memory of the Recorder, namely: "Operating Instruction.pdf" and "Operation Manual for RecManager.pdf" which are displayed in the storage device.

AGC settings to record:

- AGC 1 for quiet areas;
- AGC 2 for noisy areas;
- Long range AGC 3 with noise reduction;
- AGC 4 for large noisy areas;
- AGC 5 for a busy street.

Optional accessories:

1. Programmable remote microphone with AGC system;
2. RecAdapter (telephone conversation recorder);
3. Knowles-based remote microphone (+10dB).

Charging the Rechargeable Battery

Unscrew the Lid (see the Picture) and connect the Recorder to the USB port of the PC. While charging, the recorder's LED is flashing gradually with a five-second interval. When the rechargeable battery is fully charged the LED flashes without intervals.

In Box

1. Recorder;
2. USB cable;
3. Instructions.

For more details see Operational Manual in the internal memory of the Recorder.

It is also available on our website
www.ts-market.com

Manufacturer Warranty Coupon

The manufacturer undertakes warranty repair liabilities for 1 year from the date of purchase, but no longer than 2 years from the date of manufacture of the product (warranty does not cover batteries). Paid repair is provided within recorder's operation lifetime (5 years). The manufacturer reserves the right to refuse in repair after the expiration of recorder operation life.

This warranty is voided if the recorder is:

- improperly used;
- mechanically damaged;
- received without supplier warranty tag on this document.

All questions regarding product exchange and return must be solved with the seller's company according to Protection of Consumers Law.

Digital Recorder EDIC-mini Tiny 16 A63

- 300h
- 600h
- 1200h

Number: _____

QC: _____

Selling date: _____

Seller: _____

Address:

TS-Market Ltd.

Building 10/1 Sosnovaya Alleya, Zelenograd, Moscow,
The Russian Federation, 124489

Tel: +7 (495) 638-8800; +7 (499) 940-95-75

(Cell) +7(903) 530-10-01, +7 (909) 638-88-00

Fax: +7 (499) 735-0491

E-mail: support@ts-market.com

<http://www.ts-market.com>

GPS coordinats :

55.98065 N

37.25224 E