

EDIC-mini TINY

Model STEREO


1120/2240/4480/8960/17920

- Dimensions: 12x35x17 mm;
- Weight: 10 g;
- Recording time: up 420 hours;
- Recording mode: mono or stereo;
- Microphone sensitivity: 7...9 m;
- Operating temperature: 0-40°C (32-104°F);
- External rechargeable battery capacity: 120 mA/hour;
- Battery life:
 - In record mode (sampling rate 8 kHz, without compression, mono): up to 60 hours;
 - In stand-by mode: up to 6 months;
- Case: metallic case;
- Rechargeable battery charge: from USB socket.

Package Content

- Voice recorder;
- USB cable;
- Two external microphones;
- CD with drivers and programs;
- User manual.

Description



Labeling	Function	Parameters
OUT	Microphone's signal	Voltage 2,9Vpp, with the constant component 1,5V
GND	Global bus	
FUCC	+ microphone's power supply	Voltage 3+/-0,2 V

Before Recording

To start recording, set the Record switch in the recording position. The voice recorder starts blinking in sequence while the recording is in a progress. To stop the recording, set the Stop switch in the stop position.

Blinking sequences indicate a rechargeable battery status and available memory. The first sequence indicates a rechargeable battery status: one flash – fully charged, two flashes – enough for work, three flashes – should

be charged. The second blinking sequence indicates the amount memory is available: one flash – 76-100%, two flashes -51-75%, three flashes – 25-50%, 4 flashes – 1-25%.

To estimate the battery life in different modes, use the table below:

	Without compression	u-Law	4-bits ADPCM	2-bits ADPCM
5.5kHz	70h/52h	63h/40h	57h/37h	60h/40h
8kHz	60h/40h	52h/34h	42h/29h	48h/32h
11kHz	44h/33h	41h/24h	37h/22h	38h/22h
16kHz	33h/26h	31h/19h	27h/18h	30h/19h
22kHz	34h/20h	24h/-	22h/-	22h/-

The table shows approximate battery life for different recording modes (recording time in mono mode / recording time in stereo mode)

How to Charge a Rechargeable battery

Rechargeable battery charging is automatic while connecting a voice recorder to a USB socket of a computer. To charge a rechargeable battery fully, keep the voice recorder connected to a computer during three hours. While starting charging, an indicator is slowly blinking with five seconds interval. When the rechargeable battery is fully charged, the indicator is slowly blinking with minimal interval.

To avoid malfunctions, keep Li-ion rechargeable battery charged. Charge your rechargeable battery not rear than ones a month even if you don't use your recorder.

TS-Market Ltd.
The Manufactory Warranty Coupon

Warranty: Manufactory Warranty is 1 year from a selling date, but not more than 2 years from a date of manufacturing.

This warranty is voided if:

- Mishandling;
- Improper use;
- A product received without supplier warranty tag on this document;
- Mechanical damaged.

All questions regarding of product's exchange and return have to be solved with the seller's company according to Protection of Consumers Law.

Models:

EM Tiny STEREO - 1120, EM Tiny STEREO - 2240

EM Tiny STEREO - 4480, EM Tiny STEREO - 8960

EM Tiny STEREO - 17920

Number _____

QC _____

Selling date _____

Seller _____

Address:

TS-Market Ltd.

Building 10/1 Sosnovaya Alleya, Moscow, The Russian Federation, 124489

Tel: +7 (495) 638-8800, (495) 651-91-51. Fax: +7 (495) 535-0491

Cell phones: +7 (903) 530-10-01, +7 (909) 638-88-00

E-mail: support@ts-market.com, <http://www.ts-market.com>